Upgrade Mars 4K firmware

1. Kindly Note

- It takes a risk to to do the upgrade, please avoid updating during important events;
- Please make sure the device with enough power during updating;
- Please don't unplug the USB flash disk during updating to avoid updating failure;
- Feel free to contact us if the updating failure or error causes the malfunction: Hollyland Technical Support Engineer:support@hollyland-tech.com

2. Updating Tool

- USB-C flash disk / USB flash disk + OTG convertor
- Upgrade File

3. Upgrade Steps

1. Prepare a small USB disk(16/32G), then format it to FAT32.

Format USB Drive (F:)	USB Drive (F:) Properties					
Capacity: 7.49 GB	General Tools Hardware Sharing Customize					
File system FAT32 (Default) ~]				
Allocation unit size 4096 bytes ~	Type: USB Drive					
Restore device defaults	File system: FAT32 Used space: 17,534,976 bytes 16.7 MB					
Volume label	Free space: 8,018,722,816 bytes 7.46 GB					
Format options	Capacity: 8,036,257,792 bytes 7.48 GB					
Start Close	Drive F:					

2. Download all the upgrade files to the USB disk root directory (It will recognize automatically to upgrade)

I I I I I I I I I I I I I I I I I I I	Share	Manage View Drive Tools	USB DRIVER (H:)			- 0	× ~ ?
\leftarrow \rightarrow \checkmark \uparrow	⇒ > Th	nis PC > USB DRIVER (H:)			~ Ū	Search USB DRIVER (H:)	Q
	^	Name	^	✓ Date modified	Туре	Size	
 Quick access Desktop 	HLD_12_RX_H200_S1.0.1.1.ota	9/17/2022 5:33 PM	OTA File	30,470 KB			
🖊 Downloads	*	HLD_12_1X_H200_S	51.0.1.1.ota	9/17/2022 5:36 PM	OIA File	30,940 KB	
Documents	*						
Pictures	*						

3. Connect the USB disk to the device, it will do the upgrade automatically after turning the device on

4. Special notes

- The USB flash disk needs to be formatted into the FAT32 format first so can the device to recognize the USB flash disk.
- If the USB flash disk which over 32G, the Window/Mac system don't have the FAT32 options, so need professional disk software tools (like DiskGenius) to format it.
- The updating file needs to be placed in the USB flash disk root directory can the device read the updating file, the file can't be placed in another folder.
- Checking whether the monitor firmware version is the latest or not on the device information after the update is completed.